



肩削りカッター

 F5041 mm

 LNH . 0904 .. R
 Walter BLAXX


- チップ縦置き
- 4 コーナー使いチップ



F5041	P	M	K	N	S	H	O
	●	●	●	●	●	●	●

工具

	型番	D _c mm	d ₁ mm	l ₄ mm	l ₁ mm	L _c mm	Z	kg	チップ数	タイプ
 ScrewFit	F5041.T22.025.Z03.08	25	T22	35		8	3	0,12	3	LNH . 0904 .. R
	F5041.T22.025.Z04.08	25	T22	35		8	4	0,11	4	
	F5041.T28.032.Z04.08	32	T28	40		8	4	0,22	4	
	F5041.T28.032.Z05.08	32	T28	40		8	5	0,22	5	
 DIN 1835 B	F5041.W25.025.Z03.08	25	25	43	100	8	3	0,34	3	LNH . 0904 .. R
	F5041.W25.025.Z04.08	25	25	43	100	8	4	0,34	4	
	F5041.W32.032.Z04.08	32	32	49	110	8	4	0,61	4	
	F5041.W32.032.Z05.08	32	32	49	110	8	5	0,61	5	
	F5041.W32.040.Z06.08	40	32	49	110	8	6	0,79	6	
 Cylindrical shank	F5041.Z25.025.Z03.08	25	25	38	200	8	3	0,74	3	LNH . 0904 .. R
	F5041.Z25.025.Z04.08	25	25	38	200	8	4	0,74	4	
	F5041.Z32.032.Z04.08	32	32	39	250	8	4	1,5	4	
	F5041.Z32.032.Z05.08	32	32	39	250	8	5	1,53	5	
 Shell mill mount DIN 138 transverse keyway	F5041.B16.040.Z04.08	40	16	40		8	4	0,45	4	LNH . 0904 .. R
	F5041.B16.040.Z06.08	40	16	40		8	6	0,36	6	
	F5041.B22.050.Z05.08	50	22	40		8	5	0,49	5	
	F5041.B22.050.Z07.08	50	22	40		8	7	0,51	7	
	F5041.B22.063.Z07.08	63	22	40		8	7	0,74	7	
	F5041.B22.063.Z10.08	63	22	40		8	10	0,82	10	

バランス設計
 本体およびアセンブリー部品が納入範囲に含まれます。

D2

肩削りカッター



F5041 inch

LNH . 0904 .. R

Walter BLAXX



- チップ縦置き
- 4 コーナー使いチップ



	P	M	K	N	S	H	O
F5041	●	●	●	●	●	●	●

工具

	型番	D _c inch	d ₁ inch	l ₄ inch	l ₁ inch	L _c inch	Z	lbs	チップ数	タイプ
<p>DIN 1835 B</p>	F5041.UW26.026.Z03.08	1,000	1,000	1,719	4,000	0,315	3	0,014	3	LNH . 0904 .. R
	F5041.UW31.031.Z04.08	1,250	1,250	1,719	4,000	0,315	4	0,022	4	
<p>Cylindrical shank</p>	F5041.UZ26.026.Z03.08	1,000	1,000	1,97	8,000	0,315	3	0,029	3	LNH . 0904 .. R
<p>Shell mill mount DIN 138 transverse keyway</p>	F5041.UB19.051.Z05.08	2,000	0,750	1,575		0,315	5	0,024	5	LNH . 0904 .. R



バランス設計
 スクリュードライバーは納入範囲に含まれています。

肩削りカッター

 F5141

 LNH . 1306 .. R
 Walter BLAXX


- チップ縦置き
- 4 コーナー使いチップ



F5141	P	M	K	N	S	H	O
	●	●	●	●	●	●	●

工具

型番	D _c mm	d ₁ mm	l ₄ mm	l ₁ mm	L _c mm	Z	kg	チップ数	タイプ
F5141.T36.040.Z05.12	40	T36	40		12	5	0,36	5	LNH . 1306 .. R
F5141.T45.050.Z06.12	50	T45	40		12	6	0,51	6	
F5141.W32.040.Z03.12	40	32	49	110	12	3	0,69	3	LNH . 1306 .. R
F5141.W32.040.Z05.12	40	32	49	110	12	5	0,74	5	
F5141.Z32.040.Z03.12	40	32	44	250	12	3	1,57	3	LNH . 1306 .. R
F5141.B16.040.Z04.12	40	16	40		12	4	0,33	4	LNH . 1306 .. R
F5141.B16.040.Z05.12	40	16	40		12	5	0,33	5	
F5141.B22.050.Z05.12	50	22	40		12	5	0,35	5	
F5141.B22.050.Z06.12	50	22	40		12	6	0,53	6	
F5141.B22.063.Z06.12	63	22	40		12	6	0,8	6	
F5141.B22.063.Z08.12	63	22	40		12	8	0,71	8	
F5141.B27.080.Z07.12	80	27	50		12	7	1,29	7	
F5141.B27.080.Z10.12	80	27	50		12	10	1,27	10	
F5141.B32.100.Z09.12	100	32	50		12	9	2,72	9	
F5141.B32.100.Z13.12	100	32	50		12	13	2,68	13	
F5141.B40.125.Z11.12	125	40	63		12	11	3,3	11	
F5141.B40.125.Z16.12	125	40	63		12	16	4,35	16	

バランス設計
 本体およびアセンブリー部品が納入範囲に含まれます。



肩削りカッター

F5141

LNH . 1306 .. R
Walter BLAXX




- チップ縦置き
- 4 コーナー使いチップ



	P	M	K	N	S	H	O
F5141	●	●	●	●	●	●	●

工具



Shell mill mount DIN 138 transverse keyway

型番	D _c mm	d ₁ mm	l ₄ mm	l ₁ mm	L _c mm	Z	kg	チップ数	タイプ
F5141.B40.160.Z13.12	160	40	63		12	13	5,38	13	LNH . 1306 .. R

バランス設計
本体およびアセンブリー部品が納入範囲に含まれます。

肩削りカッター



F5141 inch

LNH . 1306 .. R

Walter BLAXX



-チップ縦置き
-4コーナー使いチップ



	P	M	K	N	S	H	O
F5141	●	●	●	●	●	●	●

工具	型番	D _c inch	d ₁ inch	l ₄ inch	l ₁ inch	L _c inch	Z	lbs	チップ数	タイプ
 ScrewFit	F5141.UT36.038.Z04.12	1,500	T36	1,575		0,472	4	0,013	4	LNH . 1306 .. R
	F5141.UW38.038.Z04.12	1,500	1,500	1,812	4,500	0,472	4	0,036	4	LNH . 1306 .. R
 DIN 1835 B	F5141.UB19.051.Z05.12	2,000	0,750	1,575		0,472	5	0,02	5	LNH . 1306 .. R
	F5141.UB26.064.Z06.12	2,500	1,000	1,575		0,472	6	0,032	6	
	F5141.UB26.076.Z07.12	3,000	1,000	1,969		0,472	7	0,052	7	
	F5141.UB31.102.Z09.12	4,000	1,250	1,969		0,472	9	0,105	9	
	F5141.UB38.102.Z09.12	4,000	1,500	2,480		0,472	9	0,135	9	
	F5141.UB38.127.Z11.12	5,000	1,500	2,480		0,472	11	0,181	11	
 Shell mill mount DIN 138 transverse keyway	F5141.UB38.152.Z13.12	6,000	1,500	2,480		0,472	13	0,238	13	LNH . 1306 .. R



スクレドドライバーは納入範囲に含まれています。
本体およびアセンブリ部品が納入範囲に含まれます。

肩削りカッター

 F5241 mm


 LNHU1607 .. R
 Walter BLAXX


- チップ縦置き
- 4 コーナー使いチップ




F5241	P	M	K	N	S	H	O
-------	---	---	---	---	---	---	---

工具



Shell mill mount DIN 138 transverse keyway






Shell mill mount DIN 138 transverse keyway

型番	D _c mm	d ₁ mm	l ₄ mm	L _c mm	Z	kg	チップ数	タイプ
F5241.B22.050.Z05.15	50	22	40	15	5	0,45	5	LNHU1607 .. R
F5241.B22.063.Z06.15	63	22	40	15	6	0,7	6	
F5241.B27.080.Z07.15	80	27	50	15	7	1,27	7	
F5241.B32.100.Z08.15	100	32	50	15	8	2,61	8	
F5241.B40.125.Z10.15	125	40	63	15	10	4,21	10	
F5241.B40.160.Z12.15	160	40	63	15	12	5,4	12	LNHU1607 .. R

バランス設計

Einbauteile			
D _c [mm]	63-160	50	
	チップ用クランプスクリュー 締め付けトルク	FS1495 (T20IP) 5 Nm	FS2112 (T20IP) 5 Nm

Zubehör			
D _c [mm]	50-125	160	
	トルクスクリュードライバー、アナログ	FS2003	FS2003
	トルクスクリュードライバー、デジタル	FS2248	FS2248
	交換ブレード	FS2015 (T20IP)	FS2015 (T20IP)
	スクリュードライバー	FS1486 (T20IP)	FS1486 (T20IP)
	(シーリング + スクリューを含む) シーリングディスクセット		FS936 SET KOMPLETT
	シーリング		O-R 96X4

型番	公差等級	コーナー数	r mm	b mm	P		M		K		N	S
					HC		HC		HC		HW	HC
					WKP25S	WKP35G	WKP35S	WSP45G	WSM35S	WSP45G	WKP25S	WKP35G
 LNHU160708R-L55T	H	4	0.8	2.3	☑	☑	☑	☑	☑	☑	☑	☑
LNHU160708R-L85T	H	4	0.8	2.3							☑	
LNHU160712R-L55T	H	4	1.2	1.9		☑	☑	☑		☑	☑	☑
LNHU160716R-L55T	H	4	1.6	1.6			☑	☑				☑

HC = コーティング超硬
HW = ノンコート超硬